

# Notice



- ☐ CORRECTION
 ☒ PRODUCTION CHANGE  
☐ SERVICE FLASH
 ☐ ADD INFORMATION

FILE NO.

REVISION 1

Please add this notice to the Service Manual listed below.

|                                     |                                               |
|-------------------------------------|-----------------------------------------------|
| Category: <b>COLOR TELEVISION</b>   | Date: <b>August / 15 / 2006</b>               |
| Model: <b>DP32746</b>               | Effective from : Chassis No. <b>P32746-01</b> |
| Destination: <b>U.S.A. / CANADA</b> | REF. No. <b>SM780112</b>                      |

**NOTE:** Match the Chassis No. on the unit's back cover with the Chassis No. in the Service Manual. **If the Service Manual Chassis No. does not match the unit's**, additional Service Literature is required. This chassis is similar to Chassis No. P32746-00. Only the **difference** Service Information is given in this manual. For detailed Service Information, refer to the **Original** Service Manual and **Notices** for Chassis No. P32746-00 used in Model DP32746 (SM780112).

**Servicing should be performed by only trained and qualified service personnel.**

## 1. IN THE CHASSIS ELECTRICAL PARTS LIST MAIN PC BOARD

The reason for change.

- A : Misprint    B : Quality Reliability    C : Standardization  
 D : Design    E : Add as a possible sub    F : Schematic location change  
 G : Purchasing Request

| Page & Section                                 | Schematic Location |     | Part No.      | Description            | Q'ty | Interchangeability | Reason |
|------------------------------------------------|--------------------|-----|---------------|------------------------|------|--------------------|--------|
| Page 10<br>Chassis<br>Electrical<br>Parts List | C1693              | Old | NA            | NOT USED               | 0    | NO                 | D      |
|                                                |                    | New | CK1H563KLZBNG | CERAMIC 0.056U K 50V   | 1    | NO                 |        |
|                                                | C1694              | Old | CEXLB1V471WAN | ELECT 470U M 35V       | 1    | NO                 | D      |
|                                                |                    | New | CEXLB1V331WAN | ELECT 330U M 35V       | 1    | NO                 |        |
| Page 12<br>Chassis<br>Electrical<br>Parts List | L1683              | Old | 1AV4L2JJ330MN | INDUCTOR, 33U M        | 1    | NO                 | D      |
|                                                |                    | New | 1AV4L2JJ470KN | INDUCTOR, 47U K        | 1    | NO                 |        |
| Page 16<br>Chassis<br>Electrical<br>Parts List | R1662              | Old | RGF8200JTCANL | MT-GLAZE 820 JA 1/10W  | 1    | NO                 | D      |
|                                                |                    | New | RGF4701JTCANL | MT-GLAZE 4.7K JA 1/10W | 1    | NO                 |        |
|                                                | R1663              | Old | NA            | NOT USED               | 0    | NO                 | D      |
|                                                |                    | New | RGF1801JTCANL | MT-GLAZE 1.8K JA 1/10W | 1    | NO                 |        |

## 1. IN THE CHASSIS ELECTRICAL PARTS LIST MAIN PC BOARD (Cont.)

The reason for change.

A : Misprint    B : Quality Reliability    C : Standardization  
D : Design    E : Add as a possible sub    F : Schematic location change  
G : Purchasing Request

| Page & Section                                 | Schematic Location |     | Part No.      | Description            | Q'ty | Interchangeability | Reason |
|------------------------------------------------|--------------------|-----|---------------|------------------------|------|--------------------|--------|
| Page 16<br>Chassis<br>Electrical<br>Parts List | R1675              | Old | RGF2701FTCANL | MT-GLAZE 2.7K JA 1/10W | 1    | NO                 | D      |
|                                                |                    | New | RGF8201FTCANL | MT-GLAZE 8.2K FA 1/10W | 1    | NO                 |        |
|                                                | R1676              | Old | RGF2700FTCANL | MT-GLAZE 270 JA 1/10W  | 1    | NO                 | D      |
|                                                |                    | New | RGF3300FTCANL | MT-GLAZE 330 JA 1/10W  | 1    | NO                 |        |
|                                                | R1686              | Old | NA            | NOT USED               | 0    | NO                 | D      |
|                                                |                    | New | RG122R0JTEANL | MT-GLAZE 22 JA 1W      | 1    | NO                 |        |
| Page 17<br>Chassis<br>Electrical<br>Parts List | A800               | Old | 1AA0B10N17400 | ASSY, PWB, MAIN        | 1    | NO                 | D      |
|                                                |                    | New | 1AA0B10N174B0 | ASSY, PWB, MAIN        | 1    | NO                 |        |

## 2. IN THE CHASSIS ELECTRICAL PARTS LIST POWER PC BOARD

The reason for change.

A : Misprint    B : Quality Reliability    C : Standardization  
D : Design    E : Add as a possible sub    F : Schematic location change  
G : Purchasing Request

| Page & Section                                 | Schematic Location |     | Part No.      | Description             | Q'ty | Interchangeability | Reason |
|------------------------------------------------|--------------------|-----|---------------|-------------------------|------|--------------------|--------|
| Page 19<br>Chassis<br>Electrical<br>Parts List | J639               | Old | 8YDX3R0       | JUMPER                  | 1    | NO                 | D      |
|                                                |                    | New | RDA2203JPCANN | CARBON 220K JA 1/2W     | 1    | NO                 |        |
|                                                | RT603              | Old | RGFR000ZTCANL | MT-GLAZE 0.000 ZA 1/10W | 1    | NO                 | D      |
|                                                |                    | New | NA            | NOT USED                | 0    | NO                 |        |
|                                                | R602               | Old | RGF2201JTCANL | MT-GLAZE 2.2K JA 1/10W  | 1    | NO                 | D      |
|                                                |                    | New | RGFR000ZTCANL | MT-GLAZE 0.000 ZA 1/10W | 1    | NO                 |        |
| Page 20<br>Chassis<br>Electrical<br>Parts List | R603               | Old | NA            | NOT USED                | 0    | NO                 | D      |
|                                                |                    | New | RGF1201JTCANL | MT-GLAZE 1.2K JA 1/10W  | 1    | NO                 |        |
|                                                | R635               | Old | RGF1202JTCANL | MT-GLAZE 12K JA 1/10W   | 1    | NO                 | D      |
|                                                |                    | New | NA            | NOT USED                | 0    | NO                 |        |

## 2. IN THE CHASSIS ELECTRICAL PARTS LIST POWER PC BOARD (Cont.)

The reason for change.

A : Misprint    B : Quality Reliability    C : Standardization  
D : Design    E : Add as a possible sub    F : Schematic location change  
G : Purchasing Request

| Page & Section                                 | Schematic Location |     | Part No.      | Description            | Q'ty | Interchange-ability | Reason |
|------------------------------------------------|--------------------|-----|---------------|------------------------|------|---------------------|--------|
| Page 19<br>Chassis<br>Electrical<br>Parts List | R636               | Old | RGF4700JTCANL | MT-GLAZE 470 JA 1/10W  | 1    | NO                  | D      |
|                                                |                    | New | NA            | NOT USED               | 0    | NO                  |        |
|                                                | R676               | Old | NA            | NOT USED               | 0    | NO                  | D      |
|                                                |                    | New | RGF1202JTCANL | MT-GLAZE 12K JA 1/10W  | 1    | NO                  |        |
| Page 20<br>Chassis<br>Electrical<br>Parts List | R1696              | Old | RGF6801JTCANL | MT-GLAZE 6.8K JA 1/10W | 1    | NO                  | D      |
|                                                |                    | New | NA            | NOT USED               | 0    | NO                  |        |
|                                                | A601               | Old | 1AA0B10N1750A | ASSY, PWB, POWER       | 1    | NO                  | D      |
|                                                |                    | New | 1AA0B10N175BA | ASSY, PWB, POWER       | 1    | NO                  |        |

## 3. IN THE CHASSIS ELECTRICAL PARTS LIST MISCELLANEOUS

The reason for change.

A : Misprint    B : Quality Reliability    C : Standardization  
D : Design    E : Add as a possible sub    F : Schematic location change  
G : Purchasing Request

| Page & Section                                 | Schematic Location |     | Part No.      | Description        | Q'ty | Interchange-ability | Reason |
|------------------------------------------------|--------------------|-----|---------------|--------------------|------|---------------------|--------|
| Page 20<br>Chassis<br>Electrical<br>Parts List | ★EL901             | Old | 1AV4T40B75500 | LCD (T315XW01 V5)  | 1    | NO                  | D      |
|                                                |                    | New | 1AV4T40B81900 | LCD (QD32HL0301--) | 1    | NO                  |        |

For parts or service contact

**Sanyo Manufacturing Corporation**  
**P.O. Box 2000**  
**3333 Sanyo Road**  
**Forrest City, Arkansas 72335-2000**

August 2006 SMC

Published in U.S.A.